
HA13151, HA13152

14 W × 4-Channel BTL Power IC



ADE-207-116
1st. Edition

Description

The HA13151/HA13152 are high output and low distortion 4 ch BTL power IC designed for digital car audio.

At 13.2 V to 4 Ω load, this power IC provides output power 14 W with 10% distortion.

Functions

- 4 ch BTL power amplifiers
- Built-in standby circuit
- Built-in muting circuit
- Built-in protection circuit (surge, T.S.D, and ASO)


Features

- Few external parts lead to compact set-area possibility
- Popping noise minimized
- Low output noise
- Built-in high reliability protection circuit



HA13151, HA13152

Block Diagram



Absolute Maximum Ratings (Ta = 25°C)

Item	Symbol	Rating	Unit	Remarks
------	--------	--------	------	---------

HITACHI

HA13151, HA13152

Operating supply voltage	V_{cc}	18	V
Supply voltage when no signal ^{*1}	V_{cc} (DC)	26	V
Peak supply voltage ^{*2}	V_{cc} (PEAK)	50	V
Output current ^{*3}	I_o (PEAK)	3	A
Power dissipation ^{*4}	P_T	83	W
Junction temperature	T_j	150	°C
Operating temperature	T_{opr}	-30 to +85	°C
Storage temperature	T_{stg}	-55 to +125	°C


Notes: 1. Tolerance within 30 seconds

2. Tolerance in surge pulse waveform

3. Value per 1 channel

4. Value when attached on the infinite heat sink plate at $T_a = 25$ °C.

The derating curve is as shown in the graph below.



HA13151, HA13152

Electrical Characteristics ($V_{CC} = 13.2$ V, $f = 1$ kHz, $R_L = 4 \Omega$, $R_g = 600 \Omega$, $T_a = 25^\circ\text{C}$)

HA13151

Item	Symbol	Min	Typ	Max	Unit	Test Conditions
Quiescent current	I_Q1	—	270	—	mA	$V_{in} = 0$
Output offset voltage	ΔV_O	-300	0	+300	mV	
Gain	G_V	30.5	32	33.5	dB	
Gain difference between channels	ΔG_V	-1.5	0	+1.5	dB	
Rated output power	P_o	—	14	—	W	$V_{CC} = 13.2$ V $THD = 10\%$, $R_L = 4 \Omega$
Max output power	$P_{o\max}$	—	22	—	W	$V_{CC} = 13.7$ V $THD = \text{Max}$, $R_L = 4 \Omega$
Total harmonic distortion	T.H.D.	—	0.05	—	%	$P_o = 3$ W
Output noise voltage	WBN	—	0.15	—	mVrms	$R_g = 0 \Omega$ $BW = 20$ to 20 kHz
Ripple rejection	SVR	—	55	—	dB	$R_g = 600 \Omega$, $f = 120$ Hz
Channel cross talk	C.T.	—	70	—	dB	$R_g = 600 \Omega$ $V_{out} = 0$ dBm
Input impedance	R_{in}	—	25	—	k Ω	
Standby current	I_Q2	—	—	200	μ A	
Standby control voltage (high)	V_{STH}	3.5	—	V_{CC}	V	
Standby control voltage (low)	V_{STL}	0	—	1.5	V	
Muting control voltage (high)	V_{MH}	3.5	—	V_{CC}	V	
Muting control voltage (low)	V_{ML}	0	—	1.5	V	
Muting attenuation	ATTM	—	70	—	dB	$V_{out} = 0$ dBm





HA13151, HA13152

HA13152

Item	Symbol	Min	Typ	Max	Unit	Test Conditions
Quiescent current	I_Q1	—	270	—	mA	$V_{in} = 0$
Output offset voltage	ΔV_O	-300	0	+300	mV	
Gain	G_V	38.5	40	41.5	dB	
Gain difference between channels	ΔG_V	-1.5	0	+1.5	dB	
Rated output power	P_o	—	14	—	W	$V_{cc} = 13.2 \text{ V}$ $\text{THD} = 10\%$, $R_L = 4 \Omega$
Max output power	$P_{o\max}$	—	22	—	W	$V_{cc} = 13.7 \text{ V}$ $\text{THD} = \text{Max}$, $R_L = 4 \Omega$
Total harmonic distortion	T.H.D.	—	0.05	—	%	$P_o = 3\%$
Output noise voltage	WBN	—	0.25	—	mVrms	$R_g = 0 \Omega$ $BW = 20 \text{ to } 20 \text{ kHz}$
Ripple rejection	SVR	—	45	—	dB	$R_g = 600 \Omega$, $f = 120 \text{ Hz}$
Channel cross talk	C.T.	—	60	—	dB	$R_g = 600 \Omega$ $V_{out} = 0 \text{ dBm}$
Input impedance	R_{in}	—	25	—	k Ω	
Standby current	I_{o2}	—	—	200	μA	
Standby control voltage (high)	V_{sth}	3.5	—	V_{cc}	V	
Standby control voltage (low)	V_{stl}	0	—	1.5	V	
Muting control voltage (high)	V_{mh}	3.5	—	V_{cc}	V	
Muting control voltage (low)	V_{ml}	0	—	1.5	V	
Muting attenuation	ATTM	—	60	—	dB	$V_{out} = 0 \text{ dBm}$

HA13151, HA13152


Pin Explanation

Pin No.	Symbol	Functions	Input Impedance	DC Voltage	Equivalence Circuit
1	IN1	CH1 INPUT	25 kΩ (Typ)	0 V	
11	IN2	CH2 INPUT			
13	IN3	CH3 INPUT			
23	IN4	CH4 INPUT			
2	STBY	Standby control	90 kΩ (at Trs. cutoff)	—	
3	OUT1 +	CH1 OUTPUT	—	$V_{CC}/2$	
5	OUT1 -				
7	OUT2 +	CH2 OUTPUT			
9	OUT2 -				
15	OUT3 +	CH3 OUTPUT			
17	OUT3 -				
19	OUT4 +	CH4 OUTPUT			
21	OUT4 -				
10	MUTE	Muting control	25 kΩ (Typ)	—	

HITACHI

HA13151, HA13152

Pin Explanation (cont)

Pin No.	Symbol	Functions	Input Impedance	DC Voltage	Equivalence Circuit
22	RIPPLE	Bias stability	—	$V_{cc}/2$	
6	PV _{cc} 1	Power of output stage	—	V_{cc}	—
18	PV _{cc} 2				—
14	INV _{cc}	Power of input stage	—	V_{cc}	—
4	CH1 GND	CH1 power GND	—	—	—
8	CH2 GND	CH2 power GND			
16	CH3 GND	CH3 power GND			
20	CH4 GND	CH4 power GND			
12	IN GND	Input signal GND	—	—	—

HA13151, HA13152

Point of Application Board Design

1. Notes on Application Board's Pattern Design

- For increasing stability, the connected line of V_{CC} and OUTGND is better to be made wider and lower impedance.
- For increasing stability, it is better to place the capacitor between V_{CC} and GND (0.1 µF) close to IC.
- For increasing stability, it is better to place C1 to C8 and R1 to R8, which are for stopping oscillation, close to IC.
- It is better to place the grounding of resistor (R_g), between input line and ground, close to INGND (Pin 12) because if OUTGND is connected to the line between R_g and INGND, THD will become worse due to current from OUTGND.




Figure 1 Notes on Application Board's Pattern Design

HA13151, HA13152

2. How to Reduce the Popping Noise by Muting Circuit

At normal operating circuit, Muting circuit operates at high speed under 1 μ s.

In case popping noise becomes a problem, it is possible to reduce the popping noise by connecting capacitor, which determines the switching time constant, between pin 10 and GND. (Following figure 2)

We recommend value of capacitor greater than 1 μ F.

Also transitional popping noise can be reduced sharply by muting before V_{CC} and Standby are ON/OFF.






Figure 2 How to use Muting Circuit

Table 1 Muting ON/OFF Time



C (μF)	ON Time	OFF Time
nothing	under 1 μ s	under 1 μ s
0.47	2 ms	2 ms
4.7	19 ms	19 ms

HA13151, HA13152




HITACHI

HA13151, HA13152





HA13151, HA13152




HITACHI

HA13151, HA13152




HA13151, HA13152




HITACHI

HA13151, HA13152





HA13151, HA13152




HITACHI

HA13151, HA13152




HA13151, HA13152




HITACHI

HA13151, HA13152




HA13151, HA13152

Cross-Talk vs. Frequency(HA13152) (3)





Cross-Talk vs. Frequency(HA13152) (4)




HITACHI

HA13151, HA13152




HA13151, HA13152



HITACHI

HA13151, HA13152



HA13151, HA13152

When using this document, keep the following in mind:

1. This document may, wholly or partially, be subject to change without notice.
2. All rights are reserved: No one is permitted to reproduce or duplicate, in any form, the whole or part of this document without Hitachi's permission.
3. Hitachi will not be held responsible for any damage to the user that may result from accidents or any other reasons during operation of the user's unit according to this document.
4. Circuitry and other examples described herein are meant merely to indicate the characteristics and performance of Hitachi's semiconductor products. Hitachi assumes no responsibility for any intellectual property claims or other problems that may result from applications based on the examples described herein.
5. No license is granted by implication or otherwise under any patents or other rights of any third party or Hitachi, Ltd.
6. MEDICAL APPLICATIONS: Hitachi's products are not authorized for use in MEDICAL APPLICATIONS without the written consent of the appropriate officer of Hitachi's sales company. Such use includes, but is not limited to, use in life support systems. Buyers of Hitachi's products are requested to notify the relevant Hitachi sales offices when planning to use the products in MEDICAL APPLICATIONS.

HITACHI

Hitachi, Ltd.

Semiconductor & IC Div.
Nippon Bldg, 2-6-2, Otemachi, Chiyoda-ku, Tokyo 100, Japan
Tel Tokyo (03) 3270-2111
Fax (03) 3270-5100

For further information write to:

Hitachi America, Ltd.
Semiconductor & IC Div.
2000 Sierra Point Parkway
Brisbane, CA. 94005-4835
U.S.A.
Tel 415-599-8300
Fax 415-593-4207

Hitachi Europe GmbH
Electronic Components Group
Continental Europe
D-85622 Fildkirchen
München
Tel 089-9 91 80-0
Fax 089-9 29 30 00

Hitachi Europe Ltd.
Electronic Components Div.
Northern Europe Headquarters
Whitebrook Park
Lower Cookham Road
Maidenhead
Berkshire SL6 8YA
United Kingdom
Tel 0628-585000
Fax 0628-779322

Hitachi Asia Pte. Ltd
#6 Collyer Quay #20-00
Hitachi Tower
Singapore 0104
Tel 535-2100
Fax 535-1533
Hitachi Asia (Hong Kong) Ltd.
Unit 705, North Tower,
World Finance Centre
Harbour City, Canton Road
Tsim Sha Tsui, Kowloon
Hong Kong
Tel 27359218
Fax 27306074

HITACHI

This datasheet has been downloaded from:

www.DatasheetCatalog.com

Datasheets for electronic components.