

SHOULDER

SHOULDER ELECTRONICS LIMITED

SPECIFICATION FOR APPROVAL

					NO:	NO 编号:		
CUSTOMER 客	户:							
PRODUCT 产	다:		SAW FII	LTER				
MODEL NO 型	号:		HDF448A	F11				
PREPARED 编	制:	Fengyu	CHEC	KED 审	核:	York		
APPROVED 批	准:	Lijiating	D A	те 🗏	期:	2007-04-03		
CUSTOMER 客户确认意见:								
CHECKED	审	核:						
APPROVED	· 批 i	准:						
DATE	日其	归:						

公司地址:广东深圳市福田区车公庙泰然工业区 303 栋 5 楼西座 West 5/F, 303 Bldg., Che Gong Miao, Industry Park, Futian Dist., Shenzhen, Guangdong, China.

Tel: 86-755-82916880 Fax: 86-755-82916881

工厂地址: 江苏无锡市滨湖经济技术开发区高运路 115 号

No. 115, Gaoyun road, Binhu Economic&Technology Development

Area, Wuxi, Jiangsu, China

Tel:86-510-5629111 Fax:86-510-5627222

Website: www. shoulder.cn

1. SCOPE


This specification shall cover the characteristics of SAW filter With F448A&AS used for the page system.

2. ELECTRICAL SPECIFICATION

DC Voltage VDC	10V
AC Voltage Vpp	10V50Hz/60Hz
Operation temperature	-20°C to +60°C
Storage temperature	-45°C to +85°C
RF Power Dissipation	0dBm

Electronic Characteristics

2-1. Typical frequency response




2-2. Electrical characteristics


Part number	F448A&AS	Unit
Nominal center frequency (Fo)	448	MHz
Insertion Loss		
1.fo-45.8~fo-39.8 MHz	50min.	dB
$2.\text{fo}\pm3.0\text{MHz}$	4.0max.	
3.fo +39.8~ fo +45.8MHz	45min.	
Ripple (with Fo ± 3.0 MHz)	2.0max	dB
Input/Output Impedance(Nominal)	50//0	Ω/pF

(Note: Operating temperature Range:-20°C to +60°C)


2. TEST CIRCUIT



4. DIMENSION



■Recommended layout of PCB(MM) (Tolerance ± 0.2MM)



5. ENVIRONMENTAL CHARACTERISTICS

5-1 High temperature exposure

Subject the filter to $+80^{\circ}$ C for 96 hours. Then release the filter into the room conditions for 1 to 2 hours prior to the measurement. It shall fulfill the specifications in table 1.

5-2 Moisture

Keep the filter at 40° C and 95% rh for 96 hours, then release the filter into the room conditions for 1 to 2 hours prior to the measurement. It shall fulfill the specifications in table 1.

5-3 Low temperature exposure

Subject the filter to -20° C for 96 hours. Then release the filter into the room conditions for 1 to 2 hours prior to the measurement. It shall fulfill the specifications in table 1.

5-4 Temperature cycling

Subject the filter to a low temperature of -55° C for 30 minutes. Following by a high temperature of $+85^{\circ}$ C for 30 Minutes. Then release the filter into the room conditions for 1 to 2 hours prior to the measurement. It shall meet the specifications in table 1.

5-5 Resistance to solder heat

Dip the filter terminals no closer than 1.5mm into the solder bath at 270 $^{\circ}$ C $\pm 10^{\circ}$ C for 10 ± 1 sec. Then release the Filter into the room conditions for 1 to 2 hours. The Filter shall meet the specifications in table 1.

5-6 Mechanical shock

Drop the filter randomly onto the concrete floor from the height of 30cm 3 times. the filter shall fulfill the specifications in table 1.

5-7 Vibration

Subject the filter to the vibration for 1 hour each in x,y and z axes with the amplitude of 1.5 mm at 10 to 55 hz. The filter shall fulfillthe specifications in table 1.

5-8 Lead fatigue

6-8-1 Pulling test

Weight along with the direction of lead without an shock 3 kg. The filter shall satisfy all the initial Characteristics.

6-8-2 Bending test

Lead shall be subject to withstand against 90°C bending in the direction of thickness. This operation shall be done toward both direction. The filter shall show no evidence of damage and shall satisfy all the initial electrical characteristics.

6. REMARK

6.1 Static voltage

Static voltage between signal load & ground may cause deterioration & destruction of the component. Please avoid static voltage.

6.2 Ultrasonic cleaning

Ultrasonic vibration may cause deterioration & destruction of the component. Please avoid ultrasonic cleaning

6.3 Soldering

Only leads of component may be soldered. Please avoid soldering another part of component.